POWER-LITE®

ID8W-WF

LED WIFI INTEGRAL DOWNLIGHT 8W—CCT

IC-4 | 5 YEAR WARRANTY | SAA | E2362

The POWER-LITE® LED Wifi Integral Downlight saves energy and costs as compared to standard halogen downlights. These come with a built-in wifi receiver for remote control via Smart Life app.

This downlight includes the elimination of UV therefore insects will not be attracted to this light.

Applications:

Domestic, Commercial & Retail.

ID-BC

ID-BLACK

Specifications

Power:	8W
LED Chip:	Epistar 2835
Colour Temperature:	Colour Changing (3000K-4000K -5700K)
Warranty:	5 Years
Life Expectancy:	40,000 Hours
Working Temperature:	-20°C to +45°C
CRI:	>80
Beam Angle:	90°
Approvals:	SAA/C-tick (RCM)
Voltage:	AC200-240V
IP Rating:	IP54
LED Driver:	Dimmable/Integral/IC-4
Connection:	1.2m Lead & Plug
Frame Colour:	White
Carton Quantity:	30

NOTES:

Note: IC-F / IC-4 rated downlights, can be covered and abutted with building materials which can be safely exposed to temperatures

Code	Frame Colour	Description	Dimensions	Cut out	Lumen Output
ID8W-WF	White	Wifi Downlight	Ø115 x 61mm	90-95mm	700-800 Lumens
ID-BC	Brushed Chrome	Ring for Downlight	-	-	-
ID-BLACK	Black	Ring for Downlight	-	-	-

NEDLANDS GROUP

Free Call: 1800 909 306

Website: nedlandsgroup.com.au

Sales: sales@nedlandsgroup.com.au

Key Features:

- WIFI control, allowing remote control, no distance limits like Bluetooth.
- Supply power and wifi then the app does the rest. (this makes it really easy to change over existing downlights)
- No wifi gateway required, app connects direct to the light via internet modem.
- Everything controlled by your phone but still compatible with a standard wall switch.
- Family Management from any device to dim and change colour temperature per room.
- Completely Zonal adjustment 5 or more at a time, even one downlight at a time.
- Master option to turn everything off at once.
- Add as many mobile devices as you like.
- You can even set valid time periods for automation to night or day.
- Dimming of the luminaire can only achieved using the app and not via a standard wall dimmer.