

# SMOKE ALARMS

## 240V MAINS POWERED



### VULCAN SERIES

#### 240V WITH OPTIONAL RF MODULE

The Vulcan Smoke Alarm is powered by 240V mains power and supported by either a 9V 1-yr or 10-yr replaceable battery back-up.

The alarm is fitted with a test/hush/silence button to facilitate testing of the alarm. The silence function also allows the alarm and alarm system to be silenced in the case of a false alarm.

Once fitted with the RF module, the alarm connects with up to 40 alarms on one wireless network. RF compatibility with the Ranger Battery Powered RF Smoke Alarm.

RF module sold separately.

#### FEATURES

- 1yr or 10yr replaceable battery back-up
- Optional RF module
- Indicator lights for test/hush/silence and fault warnings
- Loud alarm: 85dB(A) @ 3m
- CSIRO ActivFire listed
- Meets Australian smoke alarm standards (AS3786:2014)
- 7 year warranty



#### SPECIFICATIONS

<b>MODEL NUMBERS</b>	240V 1yr: EP-VC-240-10 240V 1yr: EP-VC-240-1 RF Module: EP-VC-RF-MOD
<b>NORMAL OPERATING &amp; STORAGE TEMPERATURE</b>	0° to 40°
<b>DIMENSIONS</b>	140mm x 44.9mm
<b>WEIGHT</b>	281g
<b>WARRANTY</b>	7 Years
<b>WIRELESS DISTANCE</b>	>20m (100m outside)

<b>POWER</b>	240V with 1yr 9V Alkaline or 10yr 9V lithium replaceable battery
<b>SENSOR</b>	Photoelectric optical chamber
<b>ALARM VOLUME</b>	>85dB(A) @ 3m
<b>INTERCONNECT</b>	Radio Frequency (RF) enabling connection with up to 40 alarms on one wireless network
<b>NORMAL OPERATING &amp; STORAGE HUMIDITY</b>	15% to 95% relative humidity (non-condensing)