



20W LED MICROWAVE SENSOR



B20W-CC-MS

The POWER-LITE® integrated 20W LED Batten with microwave sensor is a complete fitting replacement for existing T8 installations, or perfect for new installations looking for a complete LED solution in a single fitting.





1800 909 306 nedlandsgroup.com.au sales@nedlandsgroup.com.au








APPLICATIONS Office | Retail Healthcare Domestic

Commercial



DIMENSIONS



DIP Switch Factory Settings

Detection Area

Hold Time 3 mins Daylight Sensor 30 Lux

Stand-by Period 10 mins

Stand-by Dimming Level

LED Chip 2835 SMD

Life Expectancy 50,000 hrs TM-21

SCDM <6 Macadam steps

Working Temp -20°C to +45°C

Power Factor >0.90

CRI >80 Cable Entry Wired both from the back and the two sides

Efficacy Up to 1011m/W

EED Driver

Material Aluminium and PC

Nett Weight 1.1kg

Mount Type Surface Mounted Connection Hardwired

Battery Type Lithium

Microwave Sensor Batten is dimmable via sensor only and can't be dimmed via standard dimmer

Hold Time 3 minutes

Detection Distance 5m detection - 3m mount height

Carton Qty 6

V
2000

Image: Sector of the sector

PRODUCT

20W LED MICROWAVE SENSOR BATTEN

CODE

B20W-CC-MS



Beam Angle




1800 909 306 nedlandsgroup.com.au sales@nedlandsgroup.com.au




PHOTOMETRICS





B20W-CC-MS | 4000K

B20W-CC-MS | 6000K







1800 909 306 nedlandsgroup.com.au sales@nedlandsgroup.com.au